

ATH-350

Professional Two Way Radio

ADIN
ADINO TELECOM LIMITED

UHF TRANSRECEIVER



Compact, Reliable, Versatile

Features

- ◆ 5 Watts 16 Channels
- ◆ 2200 mAH Lithium-ion Batt. Std.
- ◆ Mil-Spec and IP - 54
- ◆ Programmable Emergency Button
- ◆ 16 Preprogrammed Channels
- ◆ Compandar Built in
- ◆ Remote Stun
- ◆ Highly Water Resistant
- ◆ Ergonomic Mechanic Design

ADINO Radio

STAY CONNECTED. STAY AHEAD

Applications

♦Hotels ♦Hospitals ♦Exhibitions ♦Amusement Parks ♦Event Management
♦Construction Sites ♦Film Shooting ♦Car Parking ♦Building Security
♦Factories ♦Stadiums ♦Malls etc...

Specifications

Frequency Range	:	350-351 MHz
No. of Channels	:	16 Channels
Channel Spacing	:	25 KHz / 12.5 KHz
Frequency Spread	:	1 MHz
Weight	:	250gm with Battery
Power Source	:	Lithium-ion
Type of emission	:	11KOF3E / 16KOF3E
Type of Operation	:	Simplex pres to talk
Dimensions	:	103mm(H) x 52mm(W) x 32mm(D)
Nominal Voltage	:	7.5V DC

Transmitter

RF Power Output	:	5/1W
Max. Frequency Deviation	:	+/-5 / 2.5 KHz
Spurious & Harmonics Suppression	:	70 db Typical
Normal Battery Drain	:	1.7 Amps in 5 Watts
Hum & Noise @ 25 KHz	:	45 db
Hum & Noise @ 12.5 KHz	:	40db

Receiver

Sensitivity	:	12 db Sinad 0.25 μ V
Squelch	:	0.20 μ V Sensitivity
Selectivity @ 25KHz	:	Better than 70 db
Selectivity @ 12.5KHz	:	Better than 65 db
Audio o/p Power	:	1Watt @ 16 ohms
Battery Drain	:	55 mA Stand by

**Standard Equipments Includes 2200mAH Lithium-ion Battery,
Antenna, Rapid Charger & Belt Clip.**

ADINO TELECOM LIMITED

www.adinotelecom.com

Regd. Office / H.O.: B - 3/4, Nandkishore Industrial Estate, Off Mahakali Caves Road, Andheri (E), Mumbai - 400 093. INDIA.
Tel.: (+91 22) 6604 4600 · Fax: (+91 22) 6604 4547 · Email: sales@adinotelecom.com / service@adinotelecom.com

Adino Telecom Limited
C/O ONIDA HOUSE, A-19 / 8-1, Mohan Co-op. Ind. Est.,
Mathura Road, Badarpur, New Delhi -110 044.
Tel.: (+91 11) 4605 6085 / 84

Adino Telecom Limited
AB / 62, Ground Floor, Sector - 1, Salt Lake,
Kolkata - 700 064.
Tel.: (+91 33) 6522 6895

Adino Telecom Limited
B - 3/4, Nandkishore Ind. Est., Off Mahakali Caves Road,
Andheri (E), Mumbai - 400 093. INDIA.
Tel.: (+91 22) 6604 4600
Fax: (+91 22) 6604 4547

Adino Telecom Limited
ONIDA HOUSE No. 71/1, Raj Ware House Complex,
Voliegerchalli, Mysore Road, Kengari Hobli,
Bangalore - 560 059